

## Data Sheet

### In-Circuit ESR & DCR Capacitor Tester

**Model 881**

#### Specifications

<b>Open circuit probe voltage</b>	15mV pp
<b>Output test frequency</b>	100 KHz sine wave

#### Measures ESR

<b>ESR range ohms</b>	0.1 – 30 (25 segment LED bar scale)
	Beeps from 1 to 5 beeps depending on ESR of capacitor

#### Measures DCR

<b>DCR range ohms</b>	0.5 – 30 flashing the LED
-----------------------	---------------------------

#### Power

	One 9V battery or an external AC adapter (9V DC 100mA 5.5mm x 2.1mm center pin+)
--	--

#### Power drain

	10mA typical
--	--------------

#### Dimensions

	1.5" x 3.8" x 5.7"
--	--------------------



### B&K Precision Corporation

22820 Savi Ranch Parkway, Yorba Linda, CA 92887  
Tel: 714-921-9095, Fax: 714-921-6422  
www.bkprecision.com

Specifications subject to change without notice